






ET5X Accessories





NOTE: This document is only for general reference. Solution Builder and related PMBs should be used for product availability, pricing, and final solution selection.


Cradles/Charging

Part Number	Picture	Description	Notes	Required Items
CRD-ET5X-1SCOM1		Single Slot Communication Dock/Cradle - Standard Connector	<ul style="list-style-type: none"> Provides charging Provides one HDMI, one Ethernet, and three USB 3.0 ports Ethernet modes 10/100/1000Mb via USB 2.0 to Ethernet adapter in dock. HDMI v1.4a, up to 1920x1080px, 60Hz. Recommend using shielded HDMI cable. USB ports can provide 900 mA max current on each port Does NOT charge spare battery. Compatible with both 8" and 10" tablets. Has standard 40-pin connector. Not compatible with devices using Rugged Frame with Rugged I/O port (SG-ET5X-8RCSE1-01/SG-ET5X-10RCSE1-01) Includes shim which should be used with devices without the Rugged Frame (SG-ET5X-8CSE1-01/SG-ET5X-10CSE1-01) attached. Dock must be powered with Power Supply for any of the ports to be operational. Dock will power down when tablet is removed or shut down. 	<ul style="list-style-type: none"> Power Supply (PWR-WGA12V60W-1WW) and AC Line Cord (23844-00-00R). <p>NOTE: Power Supply (PWRS-14000-148R) and AC Line Cord (23844-00-00R) can be used for demo purposes, but is not approved for deployments due to regulatory approvals.</p>
CRD-ET5X-1SRCOM1-01		Single Slot Communication Dock/Cradle - Rugged Connector	<ul style="list-style-type: none"> Provides charging Provides one HDMI, one Ethernet, and three USB 3.0 ports Does NOT charge spare battery. Compatible with both 8" and 10" tablets. Has Rugged POGO pin connector. Not compatible with devices without Rugged Frame and rugged I/O port Expected Q4 2015 	<ul style="list-style-type: none"> Power Supply (PWR-WGA12V60W-1WW) and AC Line Cord (23844-00-00R). <p>NOTE: Power Supply (PWRS-14000-148R) and AC Line Cord (23844-00-00R) can be used for demo purposes, but is not approved for deployments due to regulatory approvals.</p>
CRD-ET5X-SE4ENT1-01		Four Slot Ethernet Charging ShareCradle	<ul style="list-style-type: none"> Allows speeds up to 1 Gb Provides charging Does NOT charge spare battery. Compatible with both 8" and 10" tablets. Expected H1 2016 	<ul style="list-style-type: none"> Power Supply (PWRS-14000-241R), DC Line Cord (50-16002-029R), and AC Line Cord (23844-00-00R)
CRD-ET5X-SE4CO1-01		Four Slot Ethernet + Charge ShareCradle - Rugged Connector	<ul style="list-style-type: none"> Allows speeds up to 1 Gb Provides charging Does NOT charge spare battery. Compatible with both 8" and 10" tablets. Has Rugged POGO pin connector. Not compatible with devices without Rugged Frame and rugged I/O port Expected H1 2016 	<ul style="list-style-type: none"> Power Supply (PWRS-14000-241R), DC Line Cord (50-16002-029R), and AC Line Cord (23844-00-00R)




CRD-ET5X-1SCHG1		Single Slot Charge-Only Dock/Cradle	<ul style="list-style-type: none"> Provides charging Does NOT charge spare battery. Compatible with both 8" and 10" tablets. Connects to charging contacts on bottom of tablet. Compatible with devices with or without Rugged Frames 	<ul style="list-style-type: none"> Power Supply (PWR-WGA12V60W-1WW) and AC Line Cord (23844-00-00R). <p>NOTE: Power Supply (PWRS-14000-148R) and AC Line Cord (23844-00-00R) can be used for demo purposes, but is not approved for deployments due to regulatory approvals.</p>
CRD-ET5X-SE4CO1-01		Four Slot Charge-Only ShareCradle	<ul style="list-style-type: none"> Provides charging Does NOT charge spare battery. Compatible with both 8" and 10" tablets. Connects to charging contacts on bottom of tablet. Compatible with devices with or without Rugged Frames Expected H1 2016 	Power Supply (PWRS-14000-241R), DC Line Cord (50-16002-029R), and AC Line Cord (23844-00-00R)
SAC-ET5X-4PPK1-01		Four-Slot Powerpack battery charger	<ul style="list-style-type: none"> Charges up to 4 Powerpack batteries Can be used standalone or can be mounted to ShareCradle system Expected H1 2016 	Power Supply (PWRS-14000-148R) and AC Line Cord (23844-00-00R)
KT-UNIVLBRKT-01R		Multi-Slot ShareCradle Mounting Bracket	<ul style="list-style-type: none"> Allows for rack and wall mounting of all Multi-Slot ShareCradles Bracket can be mounted on standard 19" network rack or on a wall. Cable routing slots & removable power supply tray. Adjustable tabs & screw mounts for easy hanging/installation with ability to support one Multi-Slot Cradle or four 4-Slot Battery Chargers and their power supplies. 	
25-MCXUSB-01R		Micro USB Cable for Charging	<ul style="list-style-type: none"> Used to charge ET5X via the USB port on the side of the device. Does NOT provide USB communication, only charging. Can also be used to charge Powerpack Battery for Z-Back (BTRY-ET5X-PRPK1-01) via micro USB port on side of battery. NOTE: Cable uses heavier gauge wire for more efficient charging. Other micro USB cables (i.e. 25-124330-01R) may provide slower charging. 	USB Power Supply (PWRS-124306-01R) or comparable. Recommend using alternate 2 Amp power supply for faster charging.
CHG-ET5X-CBL1-01		Rugged Charge Cable	<ul style="list-style-type: none"> Connects to charge contacts on bottom of ET5X. Works with ET5X units with and without Rugged Frames. Expected Q4 2015 	<p>Power Supply</p> <p><u>For indoor use:</u> Power Supply (PWRS-14000-148R) and AC Line Cord (23844-00-00R)</p> <p><u>For in-vehicle use:</u> 12 volt vehicles - Car Charger (VCA9002-12R) 24 volt vehicles - Car Charger (VCA9000-24R)</p>

Brodit various (3rd party) http://www.proclipusa.com		Brodit/ProClip Vehicle Cradles	<ul style="list-style-type: none"> Available in both powered and un-powered versions (cigarette lighter adapter or straight through power cable) Select cradle model based on ET5X connector type (rugged/non-rugged), size (8"/10"), Expansion back, cradle key lock support. Coming soon 	
CRD-ET5X-8RMNTCOM-01 (for 8" tablet) CRD-ET5X-10RMNTCOM-01 (for 10" tablet)		Rugged Mount Forklift Charge/Communication Cradle	<ul style="list-style-type: none"> For vehicle/fork lift operations Provides 3 USB, 1 HDMI, and 1 Ethernet port Includes key lock Has Rugged POGO pin connector. Not compatible with devices without Rugged Frame and rugged I/O port Expected Q4 2015 	To Power Cradle: <ul style="list-style-type: none"> Fork Lift Power Converter (PWRS-14000-251R for high voltage vehicles OR PWRS-14000-252R for lower voltage vehicles) Fork Lift Cradle Power Cable (25-103872-01R) Rugged Frame w/Rugged I/O connector (SG-ET5X-8RCSE1-01 or SG-ET5X-10RCSE1-01)

Communication Cables




Part Number	Picture	Description	Notes	Required Items
PSA1U1E-E (3rd party) http://www.portsmith.com		daptaPort Rugged USB-A to Ethernet Adapter	<ul style="list-style-type: none"> 10/100 Mbps Ethernet with RJ45 Connection Extreme temperature ratings and sealed and enclosed electronics make for a durable solution Can connect directly to ET5X (via USB port) ET5X does not support network boot option with adapter. Use CRD-ET5X-1SCOM1 for this. 	





Attachments

Part Number	Picture	Description	Notes	Required Items
ZBK-ET5X-8RH1-01 (for 8" tablet) ZBK-ET5X-10RH1-01 (for 10" tablet)		Z-Back with Rotating Hand strap	<ul style="list-style-type: none"> No scanner Cap/Plug covers Powerpack battery compartment. Remove cap if using optional Powerpack battery (BTRY-ET5X-PRPK1-01) Expected Q4 2015 	
ZBK-ET5X-8SCN1-01 (for 8" tablet) ZBK-ET5X-10SCN1-01 (for 10" tablet)		SE4710 Z-Back with Rotating Hand strap	<ul style="list-style-type: none"> Uses SE4710 Scan engine Cap/Plug covers Powerpack battery compartment. Remove cap if using optional Powerpack battery (BTRY-ET5X-PRPK1-01) Expected Q1 2016 	
ZBK-ET5X-8SCN5-01 (for 8" tablet) ZBK-ET5X-10SCN5-01 (for 10" tablet)		SE4750 Z-Back with Rotating Hand strap	<ul style="list-style-type: none"> Uses SE4750 Scan engine Cap/Plug covers Powerpack battery compartment. Remove cap if using optional Powerpack battery (BTRY-ET5X-PRPK1-01) Expected Q4 2015 	


Soft Goods

Part Number	Picture	Description	Notes	Required Items
-------------	---------	-------------	-------	----------------




SG-ET5X-HNDSTP-01		Breakaway Handstrap	<ul style="list-style-type: none"> Expected Q4 2015 	
SG-ET5X-RHHP1-01		Replacement Rotating Hand Strap for Z-Back	<ul style="list-style-type: none"> Adjustable and 360-degree rotatable handstrap that mounts on the back of the ET5X and provides secure option for holding the device. Expected Q4 2015 	Z-Back attachment
SG-ET5X-8HLST-01 (for 8" tablet) SG-ET5X-10HLST-01 (for 10" tablet)		Operations Case	<ul style="list-style-type: none"> Allows tablet to be worn in three ways: <ol style="list-style-type: none"> on Belt on Shoulder using Strap (not included) across body using Strap (not included) Supports tablet without Rugged Frame Easily detachable belt loop Pen loop for stylus Incorporates briefcase handle Supports all installed accessories D Rings - supports wearing on shoulder, cross body etc. Supports multi-point belt loop Includes universal mounting points to accommodate CS4070 or PD40 in a separate pouch 	Universal Holster Belt (SG-UNI102000-01R) OR Universal Shoulder Strap (58-40000-007R)
SG-UNI102000-01R		Universal Holster Belt	<ul style="list-style-type: none"> Used with Operations Case 1.5" wide, 51" max. length 	
SG-ET5X-SHDRSTP-01		Breakaway Shoulder Strap	<ul style="list-style-type: none"> Used with Operations Case or Rugged Frame with D-Clips Expected Q4 2015 	
58-40000-007R		Universal Shoulder Strap	<ul style="list-style-type: none"> Used with Operations Case or Rugged Frame with D-Clips 1.5" wide, 22 to 50" max. length Does not use breakaway design 	
SG-ET5X-DCLIP-01		D-clips for Rugged Frame	<ul style="list-style-type: none"> Clips screw onto Rugged Frame and provide attachment point for Breakaway Shoulder Strap (SG-ET5X-SHDRSTP-01) or Universal Shoulder Strap Includes 2 clips Expected Q4 2015 	




SG-ET5X-8CSE1-01 (for 8" tablet)		Rugged Frame	<ul style="list-style-type: none"> Increases drop spec to 6 ft. (1.8m) Two piece design is secured around tablet with torx screws (T6 size blade) Notch in frame allows existing I/O and charging connectors on bottom of tablet to be used. 	
SG-ET5X-10CSE1-01 (for 10" tablet) Expected Q4 2015				
SG-ET5X-8RCSE1-01 (for 8" tablet)		Rugged Frame with Rugged I/O connector	<ul style="list-style-type: none"> Increases drop spec to 6 ft. (1.8m) Replaces standard I/O connector with rugged contact pad connectors Rugged POGO pin connector accessories required when using Frame Expected Q4 2015 	
SG-ET5X-10RCSE1-01 (for 10" tablet)				

Misc




Part Number	Picture	Description	Notes	Required Items
KT-ET5X-8SCRN1-01 (for 8" tablet)		Screen Protector	Expected Q4 2015	
KT-ET5X-10SCRN1-01 (for 10" tablet)				
KT-ET5X-ACTSTY1-01		Stylus	<ul style="list-style-type: none"> Active stylus Expected Q4 2015 	

Power Cords/Power Supplies

Part Number	Picture	Description	Notes	Required Items
PWRS-124306-01R		USB Power Supply	<ul style="list-style-type: none"> Used to power ET5X from Micro-USB port on side of device Can also be used to charge Powerpack Battery for Z-Back (BTRY-ET5X-PRPK1-01) via micro USB port on side of battery. Provides 1.2A output. Charging will be slower. Use alternate 2A power supply for faster charging. Includes four international plugs for use in US, UK, EU, and AU 	Micro USB Cable (25-MCXUSB-01R)
TBD		USB Power Supply (US)	<ul style="list-style-type: none"> Used to power ET5X from Micro-USB port on side of device Can also be used to charge Powerpack Battery for Z-Back (BTRY-ET5X-PRPK1-01) via micro USB port on side of battery. 5V, 2A output for quick charging May be labeled with P/N ADP-10BW B 	Micro USB Cable (25-MCXUSB-01R)
PWR-WGA12V60W-1WW		Power Supply for Single Slot Cradle/Docking Station	<ul style="list-style-type: none"> Used to power Single Slot Cradles May be labeled with P/N KPL-060F 12V, 5A output 	

PWRS-14000-148R		Power Supply with integrated DC Cord	<ul style="list-style-type: none"> Used to power Rugged Charge Cable (CHG-ET5X-CBL1-01) Can also be used to power Single Slot Cradles for demo purposes only. Not approved for deployments due to regulatory approvals. 100-240 VAC, 12VDC, 3.33A Energy Star Compliant 	
50-14000-148R		Power Supply with integrated DC Cord	<ul style="list-style-type: none"> Discontinued 12/2007 - replaced by KT-14000-148R Used to power Rugged Charge Cable (CHG-ET5X-CBL1-01) Can also be used to power Single Slot Cradles for demo purposes only. Not approved for deployments due to regulatory approvals. 	
KT-14000-148R		Power Supply with integrated DC Cord	<ul style="list-style-type: none"> Replaces 50-14000-148R Used to power Rugged Charge Cable (CHG-ET5X-CBL1-01) Can also be used to power Single Slot Cradles for demo purposes only. Not approved for deployments due to regulatory approvals. Discontinued 12/2010 - now use PWRS-14000-148R 	
50-16002-029R		DC Power Cord	Used to power Multi-Slot ShareCradles	
PWRS-14000-241R		Power Supply	<ul style="list-style-type: none"> Replaces 50-14000-241R Used to power Multi-Slot ShareCradles 100-240VAC, 12VDC, 9A Energy Star Compliant 	
50-14001-004R		Power Supply	<ul style="list-style-type: none"> Discontinued 12/2007 - replaced by 50-14000-241R Used to power Multi-Slot ShareCradles 	
50-14000-241R		Power Supply	<ul style="list-style-type: none"> Replaces 50-14001-004R Used to power Multi-Slot ShareCradles Discontinued 12/2010 - now use PWRS-14000-241R 	
23844-00-00R		AC Line Cord		
25-103872-01R		Fork Lift Cradle Power Cable	Connects Fork Lift Cradle Power Converter to Fork Lift Cradle	
PWRS-14000-251R		Fork Lift Cradle High Voltage Power Converter	<ul style="list-style-type: none"> Replaces 50-14000-251R, meets regulatory requirements for use in EU countries. Supports 36, 48, 60 nominal VDC fork lift vehicles. 18-75VDC, 12VDC Energy Star Compliant 	

50-14000-251R		Fork Lift Cradle High Voltage Power Converter	<ul style="list-style-type: none"> Supports 36, 48, 60 nominal VDC fork lift vehicles. Discontinued 12/2010, now use PWRS-14000-251R 	
PWRS-14000-252R		Fork Lift Cradle Low Voltage Power Converter	<ul style="list-style-type: none"> Replaces 50-14000-252R, meets regulatory requirements for use in EU countries. Supports 12, 24 nominal VDC fork lift vehicles. 9-30VDC, 12VDC Energy Star Compliant 	
50-14000-252R		Fork Lift Cradle Low Voltage Power Converter	<ul style="list-style-type: none"> Supports 12, 24 nominal VDC fork lift vehicles. Discontinued 12/2010, now use PWRS-14000-252R 	
VCA9002-12R		12V Car Charger	<ul style="list-style-type: none"> Used to charge unit's battery in a vehicle. Plugs into cigarette lighter. Improvements made to the fuse holder retention to eliminate possibility of it opening with continuous insertion and removals. Complies with the UL60950 standard and has a CB test certificate 	Rugged Charge Cable (CHG-ET5X-CBL1-01)
VCA9001-12R		12V Car Charger	<ul style="list-style-type: none"> Used to charge unit's battery in a vehicle. Plugs into cigarette lighter. Improvements made to the fuse holder retention to eliminate possibility of it opening with continuous insertion and removals. Discontinued 8/31/2012 or while supplies last, now use VCA9002-12R 	Rugged Charge Cable (CHG-ET5X-CBL1-01)
VCA9000-12R		12V Car Charger	<ul style="list-style-type: none"> Used to charge unit's battery in a vehicle. Plugs into cigarette lighter. Discontinued 10/2010, now use VCA9001-12R 	Rugged Charge Cable (CHG-ET5X-CBL1-01)
VCA9000-24R		24V Car Charger	<ul style="list-style-type: none"> Used to charge unit's battery in a vehicle. Plugs into cigarette lighter. Used with higher voltage vehicles 	Rugged Charge Cable (CHG-ET5X-CBL1-01)
Batteries				
Part Number	Picture	Description	Notes	Required Items

BTRY-ET5X-8IN1-1		Spare Internal Battery for 8" tablet (5900 mAh)	<ul style="list-style-type: none"> ►This is the main battery that is internal to the ET5X ►Provides 5-6 hrs continuous WLAN usage with display on OR 4-5 hrs continuous WAN usage with display on 	
BTRY-ET5X-10IN1-1		Spare Internal Battery for 10" tablet (8700 mAh)	<ul style="list-style-type: none"> ►This is the main battery that is internal to the ET5X ►Provides 8-9 hrs continuous WLAN usage with display on OR 7-8 hrs continuous WAN usage with display on 	
BTRY-ET5X-PRPK1-01		Powerpack Battery for Z-Back (6800 mAh)	<ul style="list-style-type: none"> ►Designed for use with optional Z-Back ►Hot swappable enables 24x7 usage ►This battery rapid charges the ET5X's internal main battery. ►Has 5 LED indicators for charge status ►Micro-USB port allows battery to be charged while not attached to ET5X. ►Recommend using USB charger providing 2 Amp for faster charging. ►Expected Q4 2015 	Z-Back attachment
KT-ET5X-8BTDR1-01 (for 8" tablet) KT-ET5X-10BTDR1-01 (for 10" tablet)		Replacement Main/Internal Battery Door		